

SKP32C84 SKP Board					BILL OF MATERIALS			Rev. 1.0	DATE
ITEM NO	DNP	DESCRIPTION	Designators	QTY PER	Mfg	Mfg P/N	Vendor	Vendor P/N	PACKAGE TYPE
1									
2		84 MCU	U2	1	Renesas	M30845FJGP#D9			144P6Q-A
4		Thermistor 10K Ohm	RT1	1	BC Comp	2322 640 66103	Digikey	BC1482-ND	805
5		Pot 10K Ohm	R9,16	2	Bourns	3352T-1-103	Digikey	3352T-103-ND	See Drawing
6									
7		Resistor 680 Ohm	R1,5,6,21	4	Panasonic	ERJ-6GEYJ681V	Digikey	P680ATR-ND	805
8		Resistor 10K Ohm	R2,3,4,7,8,10,11,12,20,22	10	Panasonic	ERJ-6GEYJ103V	Digikey	P10KATR	805
9		Resistor 0 Ohm	R13,14,23,24,25,26,27,28	8	Panasonic	ERJ-6GEY00V	Digikey	P0.0ATR	805
10		Resistor 7.32K	R15	1	Panasonic	ERJ-6ENF7321V		P7.32KCTR-ND	
11		Resistor 100K Ohm	R17	1	Panasonic	ERJ-6GEYJ104V	Digikey	P100KATR	805
12		Resistor 47K Ohm	R19	1	Panasonic	ERJ-6GEYJ473V	Digikey	P47KATR	805
13									
14		Capacitor 2.2 uF 16V	C1	1	Panasonic	ECS-T1CY225R	Digikey	PCS3225TR	EIA-A
15		Capacitor 0.1uF 16V ceramic	C2,3,4,5,8,11	6	Panasonic	ECJ-2VB1C104K	Digikey	PCC1812TR	805
16		Capacitors 18pF 50V ceramic	C6,7	2	Panasonic	ECJ-2VC1H180J	Digikey	PCC180CNTR-ND	805
17		Capacitors 33pF 50V ceramic	C9,10	2	Panasonic	ECJ-2VC1H330J	Digikey	PCC330CGTR	805
18									
19		Green LED Thru-holle	D3	1	Panasonic	LN38GP	Digikey	P364-ND	T1
20		Red LED Thru-holle	D1,5	2	Panasonic	LN28RP	Digikey	P363-ND	T1
21		Yellow LED Thru-holle	D2	1	Panasonic	LN48YP	Digikey	P365-ND	T1
22									
23		Switich, Pushbutton	S1,S2,S3	3		EVQ-PAC04M	Digikey	P8006S-ND	
24		Switich, Pushbutton	S4	1		EVQ-PUC02K	Digikey	P10849STR-ND	
25									
26		Diode, Common Cathode Schottky	D4	1	Diodes, Inc	BAT54C-7	Digikey	BAT54CDITR-ND	SOT23
27									
28		2 Pin Header	JP1,2	2	Sullins	PTC02SAAN	Digikey	S1012-02-ND	
29		Header 5 X 2	J7	1	AMP	103308-1	Digikey	A26267-ND	100 mil
30									
31		Crystal 8 MHz	Y2	1	ECS Inc	ECS-80-18-4	Digikey	X164-ND	HC-49US
32		Crystal 32 kHz	Y1	1	Citizen	CFS206-32.768KDZF	Digikey	300-1002-ND	cylinder
33									
34		Test Point, Black	TP1	1	Keystone	5011.00	Digikey	5011K-ND	See Drawing
35		LCD	LCD1	1	AZ Displays	ACM802B			
36		7X2 Socket	H2	1	Samtec	SLW-107-01-T-D			100 MIL
37		7X2 Header	H1	1	Samtec	TLW-107-05-T-D			
38									
39									
40		Shunts	For item 28	2	Sullins	STC02SYAN	Digikey	S9000-ND	100 MIL
41		Bump-ons	H3	5	3M	3MSJ5018BLKC	Jameco	142682	See Drawing
42			1 Bump-on applied to back of LCD						
43									
44									
45									
46	*	Do Not Populate	R18,29,30,31,32						
47									
48									
49		2883 SKP Board		1	Renesas	RDECE2883			
50									
51									
52									
53									
54									
55									
		* Indicates Do Not Populate							

Revision 1.0 Initial Release

Revision 1.1 Changed quantity item 12 was 2